


SMD POWER INDUCTOR



Various high power inductors are superior to be high saturation for surface mounting .

Directly connected electrode on ferrite core.

Highly accurate dimensions for automatic mounting





Applications:



Power supply for VTR; OA equipment; Digital camera; LCD television set notebook computers;

Portable communication equipments; DC/DC converters, etc.



Shape and Dimensions (Unit : mm)




P / N	H3
DRRI124	4.5MAX
DRRI125	6.0MAX
DRRI127	8.0MAX



P / N	H2
DRRI73	3.4MAX
DRRI74	4.5MAX



P / N	H1
DRRI62B	3.0MAX
DRRI64B	5.0MAX



P / N	H	I	J
DRRI62B / 64B	1.9	1.4	4.6
DRRI73 / 74	2.2	1.6	4.8
DRRI124 / 125 / 127	5.4	2.9	7.0

Part Number	Inductance	Rated current ranges
SDRRI62B	2.9~330uH	1.94~0.19A
SDRRI64B	10~1000uH	1.35~0.14A
SDRRI73	10~1000uH	1.68~0.16A
SDRRI74	10~1000uH	1.84~0.18A
SDRRI124	3.9~330uH	6.5~0.5A
SDRRI125	1.3~1000uH	8.0~0.4A
SDRRI127	1.2~1000uH	9.8~0.55A

SUOTEK ELECTRONICS COMPANY LIMITED

Tel: 86-769-86318023 Fax : 86-769-86318022 Website: www.suotek.com E-mail: sales@suotek.com

SDDR1009